HF38F

SUBMINIATURE INTERMEDIATE POWER RELAY



File No.:F133481



File No.:R50172340



File No.:CQC02001001944



Features

- 5A switching capability
- 1 Form A and 1 Form C
- Standard and sensitive coils available
- Plastic sealed and flux proofed types available
- Environmental friendly product (RoHS compliant)
- Outline Dimensions: (20.5 x 10.5 x 20.5) mm

CONTACT DATA				
Contact arrangement	1A, 1C			
Contact resistance	100mΩ (at 1A 6VDC)			
Contact material	See ordering info.			
Contact rating (Res. load)	NO: 5A 250VAC/30VDC NC: 3A 250VAC/30VDC			
Max. switching voltage	250VAC / 30VDC			
Max. switching current	5A			
Max. switching power	1250VA / 150W			
Mechanical endurance	1 x 10 ⁷ ops			
Electrical endurance	1 x 10 ⁵ ops			

COIL DATA	at 23°C
-----------	---------

Standard Type

Nominal Voltage VDC	Pick-up Voltage VDC	Drop-out Voltage VDC	Max. Allowable Voltage VDC	Coil Resistance Ω
3	2.1	0.15	3.9	25 x (1±10%)
5	3.5	0.25	6.5	69 x (1±10%)
6	4.2	0.30	7.8	100 x (1±10%)
9	6.3	0.45	11.7	225 x (1±10%)
12	8.4	0.60	15.6	400 x (1±10%)
18	12.6	0.90	23.4	900 x (1±10%)
24	16.8	1.20	31.2	1600 x (1±10%)
48	33.6	2.40	62.4	6400 x (1±10%)

CHARACTERISTICS

Insulation resistance		1000MΩ (at 500VDC)
Dielectric	Between coil & contacts	2000VAC 1min
strength	Between open contacts	1000VAC 1min
Operate ti	me (at nomi. volt.)	10ms max.
Release time (at nomi. volt.)		5ms max.
Humidity		45% to 85% RH
Ambient temperature		-40°C to 85°C
Shock resistance	Functional	98m/s ²
	Destructive	980m/s ²
Vibration resistance		10Hz to 55Hz 3.3mm DA
Termination		PCB
Unit weight		Approx. 8g
Construction		Plastic sealed, Flux proofed

Notes: 1) The data shown above are initial values.

2) Please find coil temperature curve in the characteristic curves below.

COIL		
Coil power	Standard: 360mW;	Sensitive: 250mW


Sensitive Type

Nominal Voltage VDC	Pick-up Voltage VDC	Drop-out Voltage VDC	Max. Allowable Voltage VDC	Coil Resistance Ω
3	2.2	0.15	3.9	36 x (1±10%)
5	3.6	0.25	6.5	100 x (1±10%)
6	4.3	0.30	7.8	145 x (1±10%)
9	6.5	0.45	11.7	325 x (1±10%)
12	8.6	0.60	15.6	575 x (1±10%)
18	13.0	0.90	23.4	1300 x (1±10%)
24	17.3	1.20	31.2	2310 x (1±10%)
48	34.6	2.40	62.4	9220 x (1±10%)



SAFETY APPROVAL RATINGS			
1 Form A UL/CUL 1 Form C		AgCdO	5A 250VAC/30VDC
	1 Form A	AgNi AgSnO2	5A 250VAC
	A = 0.10	NO: 5A 250VAC/30VDC	
	4.5	AgCdO	NC: 3A 250VAC/30VDC
	1 Form C	AgNi AgSnO2	5A 250VAC
1 Form A 1 Form C	AgCdO AgNi	5A 250VAC/30VDC at 85°C	
	AgCdO	AgCdO	NO: 5A 250VAC/30VDC at 85°C
	1 Form C	1 Form C AgNi	NC: 3A 250VAC/30VDC at 85°C

Notes: Only some typical ratings are listed above. If more details are required, please contact us.




Notes: 1) Under the ambience with dangerous gas like H₂S, SO₂ or NO₂, plastic sealed type is recommended; Please test the relay in real applications.

If the ambience allows, flux proofed type is preferentially recommended.

If water cleaning is required after the relay is assembled on PCB, please contact us for suggestion about suitable parts.


in water dealing to required and the roley to december of the D, produce contact to the degree and the analysis

OUTLINE DIMENSIONS, WIRING DIAGRAM AND PC BOARD LAYOUT



Unit: mm

1 Form C




Remark: 1) In case of no tolerance shown in outline dimension: outline dimension ≤1mm, tolerance should be ±0.2mm; outline dimension >1mm and ≤5mm, tolerance should be ±0.3mm; outline dimension >5mm, tolerance should be ±0.4mm.


- 2) The tolerance without indicating for PCB layout $% \left(1\right) =100$ is always ± 0.1 mm.
- 3) The width of the gridding is 2.54mm.

CHARACTERISTIC CURVES

ENDURANCE CURVE



COIL TEMPERATURE RISE



Disclaimer

This datasheet is for the customers' reference. All the specifications are subject to change without notice.

We could not evaluate all the performance and all the parameters for every possible application. Thus the user should be in a right position to choose the suitable product for their own application. If there is any query, please contact Hongfa for the technical service. However, it is the user's responsibility to determine which product should be used only.

© Xiamen Hongfa Electroacoustic Co., Ltd. All rights of Hongfa are reserved.